

REDUCED-ORDER PERFECT NONLINEAR OBSERVERS OF FRACTIONAL DESCRIPTOR DISCRETE-TIME NONLINEAR SYSTEMS

TADEUSZ KACZOREK ^a

^aFaculty of Electrical Engineering
Białystok Technical University, Wiejska 45D, 15-351 Białystok, Poland
e-mail: kaczonek@ee.pw.edu.pl

The purpose of this work is to propose and characterize fractional descriptor reduced-order perfect nonlinear observers for a class of fractional descriptor discrete-time nonlinear systems. Sufficient conditions for the existence of these observers are established. The design procedure of the observers is given and demonstrated on a numerical example.

Keywords: fractional, descriptor, nonlinear, discrete-time, design, reduced-order, perfect observer.

1. Introduction

Fractional linear systems have been considered in many papers and books (Kaczorek, 2013; 2008; 2012b; 2011a; 2011b; Oldham and Spanier, 1974; Ostalczyk, 2008; Podlubny, 1999; Vinagre *et al.*, 2002). Positive linear systems consisting of n subsystems with different fractional orders were proposed by Kaczorek (2011a; 2011b). Descriptor (singular) linear systems were investigated by Cuihong (2012), Dodig and Stosic (2009), Dai (1989), Duan (2010), Fahmy and O'Reill (1989), Gantmacher (1959), Kaczorek (2012b; 2013; 2004; 1992; 2012a), Kucera and Zagalak (1988), Lewis (1983), Luenberger (1977; 1978), Sajewski (2016), Van Dooren (1979) or Virnik (2008), and the positivity and stability of fractional descriptor time-varying discrete-time linear by Kaczorek (2016c), who also addressed the eigenvalues and invariants assignment by state and input feedbacks (Kaczorek, 2004; 1992; 2011b). The computation of Kronecker's canonical form of a singular pencil was analyzed by Van Dooren (1979).

A new concept of perfect observers for linear continuous-time systems was proposed Kaczorek (2001) and N'Doye *et al.* (2013). Observers for fractional linear systems were addressed by Kaczorek (2014b), Kociszewski (2013), and N'Doye *et al.* (2013) and for descriptor linear systems by Kaczorek (2015), who also discussed perfect nonlinear observers of descriptor nonlinear systems (Kaczorek, 2016a; 2016b). Fractional descriptor full-order observers for fractional

descriptor continuous-time linear systems were proposed by Kaczorek (2014a), along with reduced-order observers (Kaczorek, 2016d; 2014). Stability of positive descriptor systems was investigated by Virnik (2008).

In this paper reduced-order perfect nonlinear observers for fractional descriptor nonlinear discrete-time systems will be proposed, conditions for their existence will be established and a design procedure will be given.

The paper is organized as follows. In Section 2 conditions for the existence of perfect full-order nonlinear observers for fractional descriptor nonlinear systems will be given. Conditions for the existence of reduced-order perfect observers of fractional discrete-time nonlinear systems will be established in Section 3. A design procedure and an illustrating numerical example for reduced-order perfect nonlinear observers will be presented in Section 4. Concluding remarks will be given in Section 5.

The following notation will be used: \mathbb{R} , the set of real numbers; $\mathbb{R}^{n \times m}$, the set of $n \times m$ real matrices; I_n , the $n \times n$ identity matrix; \mathbb{Z}_+ , the set of nonnegative integers.

2. Perfect fractional discrete-time nonlinear observers

Consider the fractional descriptor discrete-time nonlinear system

$$E\Delta^\alpha x_{i+1} = Ax_i + f(x_i, u_i), \quad i \in \mathbb{Z}_+, \quad (1a)$$

$$y_i = Cx_i, \quad (1b)$$

where $x_i \in \mathbb{R}^n$, $u_i \in \mathbb{R}^m$, $y_i \in \mathbb{R}^p$ are respectively the state, input and output vectors and $E, A \in \mathbb{R}^{n \times n}$, $C \in \mathbb{R}^{p \times n}$, $f(x_i, u_i) \in \mathbb{R}^n$ is a continuous nonlinear vector function of x_i and u_i ,

$$\Delta^\alpha x_i = \sum_{j=0}^i (-1)^j \binom{\alpha}{j} x_{i-j}, \quad (2a)$$

$$\binom{\alpha}{j} = \begin{cases} 1 & \text{for } j = 0, \\ \frac{\alpha(\alpha-1)\dots(\alpha-j+1)}{j!} & \text{for } j = 1, 2, \dots \end{cases} \quad (2b)$$

$\alpha \in \mathbb{R}$ is the fractional order difference of x_i .

Substituting (2) into (1) we obtain

$$Ex_{i+1} = A_\alpha x_i + \sum_{j=2}^{i+1} c_j Ex_{i-j+1} + f(x_i, u_i), \quad (3a)$$

where

$$A_\alpha = A + E\alpha, c_j = (-1)^{j+1} \binom{\alpha}{j}. \quad (3b)$$

It is assumed that

$$\det E = 0, \quad \det[Ez - A] \neq 0. \quad (4)$$

for some $z \in \mathbb{C}$.

Definition 1. The fractional descriptor discrete-time nonlinear system

$$\begin{aligned} E\hat{x}_{i+1} &= F\hat{x}_i + \sum_{j=2}^{i+1} c_j E\hat{x}_{i-j+1} \\ &\quad + f(x_i, u_i) + Hy_i, \end{aligned} \quad (5)$$

where \hat{x}_i is the estimate of x_i , u_i and $f(x_i, u_i)$, y_i are the same vectors as in (1), $E, F \in \mathbb{R}^{n \times n}$, $\det E = 0$, $H \in \mathbb{R}^{n \times p}$ is called a (full-order) perfect observer for the system (1) if

$$\hat{x}_i = x_i \quad \text{for } i = 1, 2, \dots \quad (6)$$

The following elementary row (column) operations will be used (Kaczorek, 1992):

1. Multiplication of the i -th row (column) by a real number c . Here and subsequently this operation will be denoted by $L[i \times c](R[i \times c])$.
2. Addition of the j -th row (column) multiplied by a real number c to the i -th row (column). This operation will be denoted by $L[i+j \times c](R[i+j \times c])$.
3. Interchange of the i -th and j -th rows (columns). This operations will be denoted by $L[i, j](R[i, j])$.

Lemma 1. If

$$\text{rank} E = r < n, \quad (7)$$

then through elementary row and column operations the matrix E can be reduced to the following upper triangular form:

$$\begin{aligned} N = PEQ &= \begin{bmatrix} 0 & E_{12} \\ 0 & 0 \end{bmatrix}, \\ E_{12} &= \begin{bmatrix} e_{11} & e_{12} & \dots & e_{1r} \\ 0 & e_{22} & \dots & e_{2r} \\ \vdots & \vdots & \ddots & \vdots \\ 0 & 0 & \dots & e_{rr} \end{bmatrix}, \end{aligned} \quad (8)$$

where P and Q are matrices of the elementary row and column operations.

Proof. If (7) is satisfied, then by elementary row and column operations the matrix E can be reduced to the form

$$\begin{bmatrix} 0 & E'_{12} \\ 0 & 0 \end{bmatrix}, \quad E'_{12} \in \mathbb{R}^{r \times r}. \quad (9)$$

Next, applying elementary column operations, we can reduce the matrix E'_{12} to the upper triangular form E_{12} . ■

Definition 2. The smallest nonnegative integer q is called the nilpotent index of a nilpotent matrix N if $N^q = 0$ and $N^{q-1} \neq 0$.

Lemma 2. (Kaczorek, 2016b) If

$$\text{rank } E = r < \frac{n}{2}, \quad (10)$$

then the nilpotent index q of the matrix E is

$$q = 2 \quad \text{for } r = 1, 2, \dots, \frac{n}{2} - 1. \quad (11)$$

Lemma 3. (Kaczorek, 2016a) If (7) is satisfied and N is the nilpotent matrix (8), then the equation

$$\begin{aligned} Nx_{i+1} &= Dx_i, \\ x_i &= [x_{1,i} \quad x_{2,i} \quad \dots \quad x_{n,i}]^T, \quad i \in \mathbb{Z}_+ \end{aligned} \quad (12)$$

for a nonsingular diagonal matrix

$$D = \text{diag}[d_1 \quad \dots \quad d_n], \quad (13)$$

with $d_k \neq 0$, $k = 1, \dots, n$ has zero solution $x_i = 0$ for $i = 1, 2, \dots$.

Theorem 1. (Kaczorek, 2016a) The perfect observer (5) of the fractional descriptor nonlinear system (1) exists if and only if

$$\text{rank} \begin{bmatrix} \bar{A} - D \\ \bar{C} \end{bmatrix} = \text{rank } \bar{C}, \quad (14)$$

where $\bar{A} = PA_\alpha Q$, $\bar{C} = CQ$ and the matrices P, Q are defined by (8).

To design the perfect observer (5) for the fractional descriptor nonlinear system (1) with given matrices A, C we have to choose the matrices F, H of the observer so that the conditions (14) and $\bar{F} = D$ are satisfied. Note that the conditions are met if and only if

$$\bar{A} - \bar{H}\bar{C} = D, \quad (15)$$

where $\bar{H} = PH$.

By the Kronecker–Capelli theorem, Eqn. (15) has a solution \bar{H} for given \bar{A}, \bar{C} and D if and only if the condition (14) is satisfied. Therefore, we have the following procedure for designing of the perfect observer (5) for the nonlinear system (1).

Procedure 1.

1. Find matrices P and Q of elementary row and column operations reducing the matrix E to its nilpotent form $N = PEQ$.
2. Using $\bar{A} = PA_\alpha Q$ and $\bar{C} = CQ$ compute the matrices \bar{A} and \bar{C} .
3. Choose a diagonal matrix D so that the condition (14) is satisfied.
4. Find the solution \bar{H} of Eqn. (15) for given \bar{A}, \bar{C} and D .
5. Compute the matrices

$$F = A_\alpha - HC, \quad H = P^{-1}\bar{H} \quad (16)$$

of the perfect observer (5).

3. Reduced-order perfect observers of fractional discrete-time nonlinear systems

Consider the fractional descriptor discrete-time nonlinear system described by (3) and (1b). If

$$\text{rank } C = p, \quad (17)$$

then there exists an elementary column operation matrix Q_1 such that (Kaczorek, 1992)

$$\bar{C} = CQ_1 = \begin{bmatrix} I_p & 0 \end{bmatrix}. \quad (18)$$

Substituting

$$x = Q_1 \bar{x} \quad (19)$$

into (1b) and using (18), we obtain

$$\begin{aligned} y_i &= Cx_i = CQ_1 \bar{x}_i = \begin{bmatrix} I_p & 0 \end{bmatrix} \begin{bmatrix} \bar{x}_{1,i} \\ \bar{x}_{2,i} \end{bmatrix} \\ &= \bar{x}_{1,i}, \quad \bar{x}_{1,i} \in \mathbb{R}^p, \quad \bar{x}_{2,i} \in \mathbb{R}^{n-p}. \end{aligned} \quad (20)$$

From (20) it follows that for given y the subvector $\bar{x}_{1,i} \in \mathbb{R}^p$ is known. Therefore, the reduced-order observer of the fractional descriptor nonlinear system (1) should reconstruct only the subvector $\bar{x}_{2,i} \in \mathbb{R}^{n-p}$.

It is assumed that there exists a matrix of elementary row operations P_1 such that

$$\begin{aligned} P_1 EQ_1 &= \begin{bmatrix} E_{11} & 0 \\ E_{21} & E_{22} \end{bmatrix}, \\ E_{11} &\in \mathbb{R}^{p \times p}, \quad E_{22} \in \mathbb{R}^{(n-p) \times (n-p)}, \end{aligned} \quad (21a)$$

$$\begin{aligned} P_1 A_\alpha Q_1 &= \begin{bmatrix} A_{11} & A_{12} \\ A_{21} & A_{22} \end{bmatrix}, \\ A_{11} &\in \mathbb{R}^{p \times p}, \quad A_{22} \in \mathbb{R}^{(n-p) \times (n-p)}, \end{aligned} \quad (21b)$$

$$\begin{aligned} P_1 f(x_i, u_i) &= \begin{bmatrix} f_1(\bar{x}_{1,i}, u_i) \\ f_2(\bar{x}_{2,i}, u_i) \end{bmatrix}, \\ f_1(\bar{x}_{1,i}, u_i) &\in \mathbb{R}^p, \quad f_2(\bar{x}_{2,i}, u_i) \in \mathbb{R}^{n-p}. \end{aligned} \quad (21c)$$

Premultiplying (3a) by the matrix P_1 and using (20) and (21), we obtain

$$\begin{aligned} E_{11} \bar{x}_{1,i+1} &= A_{11} \bar{x}_{1,i} + A_{12} \bar{x}_{2,i} \\ &+ \sum_{j=2}^{i+1} c_j E_{11} \bar{x}_{1,i-j+1} + f_1(\bar{x}_{1,i}, u_i), \end{aligned} \quad (22a)$$

$$\begin{aligned} E_{21} \bar{x}_{1,i+1} + E_{22} \bar{x}_{2,i+1} &= A_{21} \bar{x}_{1,i} + A_{22} \bar{x}_{2,i} \\ &+ \sum_{j=2}^{i+1} c_j (E_{21} \bar{x}_{1,i-j+1} + E_{22} \bar{x}_{2,i-j+1}) \\ &+ f_2(\bar{x}_{2,i}, u_i). \end{aligned} \quad (22b)$$

Defining

$$\begin{aligned} \bar{y}_i &= E_{11} \bar{x}_{1,i+1} - A_{11} \bar{x}_{1,i} \\ &- \sum_{j=2}^{i+1} c_j E_{11} \bar{x}_{1,i-j+1} \end{aligned} \quad (23a)$$

$$\begin{aligned} \bar{f}_2(\bar{x}_{2,i}, u_i) &= f_2(\bar{x}_{2,i}, u_i) + A_{21} \bar{x}_{1,i} \\ &+ \sum_{j=2}^{i+1} c_j E_{21} \bar{x}_{1,i-j+1} \\ &- E_{21} \bar{x}_{1,i+1} \end{aligned} \quad (23b)$$

as the output and input of the subsystem, respectively,

from (22) we obtain

$$E_{22}\bar{x}_{2,i+1} = A_{22}\bar{x}_{2,i} + \sum_{j=2}^{i+1} c_j E_{22}\bar{x}_{2,i-j+1} + \bar{f}_2(\bar{x}_i, u_i), \quad (24a)$$

$$\bar{y}_i = A_{12}\bar{x}_{2,i}. \quad (24b)$$

If $\det E_{22} \neq 0$, then premultiplying (23a) by $\det E_{22}^{-1}$ we obtain the standard fractional discrete-time nonlinear system which can be analyzed by the well-known method (Kaczorek, 2016a).

Let

$$\text{rank } E_{22} = r < n - p. \quad (25)$$

In this case the method presented in Section 2 can be used to design the perfect descriptor fractional nonlinear observer to the nonlinear system (1).

Therefore, the following theorem has been proved.

Theorem 2. A reduced-order perfect nonlinear observer for the fractional descriptor nonlinear system (1) exists if the following conditions are satisfied:

1. The condition (17) is met.
2. There exists a matrix P_1 of elementary row operations such that (21) is satisfied.
3. The condition (25) is met.
4. The condition (14) is satisfied for the subsystem (24).

4. Design procedure and an illustrating example

From Section 3 we have the following procedure for designing the perfect nonlinear observer for the fractional descriptor nonlinear system (24).

Procedure 2.

1. Using elementary column operations, find a matrix Q_1 satisfying the condition (18) and a subvectors $\bar{x}_{1,i} \in \mathbb{R}^p$ and $\bar{x}_{2,i} \in \mathbb{R}^{n-p}$.
2. Find the output \bar{y}_i and the input $\bar{f}_2(\bar{x}_i, u_i)$ defined by (23) and the equations of the subsystem (24).
3. Using Procedure 1, find the desired perfect observer of the subsystem (24).

Example 1. Consider the fractional descriptor nonlinear

system (1) with $\alpha = 0.5$ and

$$\begin{aligned} E &= \begin{bmatrix} 0 & 0 & 0 & 1 \\ 0 & 1 & 0 & 0 \\ 1 & 2 & 0 & 1 \\ 0 & -1 & 0 & 0 \end{bmatrix}, \\ A &= \begin{bmatrix} 1 & 0 & 0 & 1 \\ 0 & 0 & 1 & 0 \\ -1 & 1 & 0 & 0 \\ 0 & 2 & 1 & 1 \end{bmatrix}, \\ C &= \begin{bmatrix} 0 & 0 & 0 & 1 \\ 2 & 1 & 0 & 2 \end{bmatrix}, \\ f(x_i, u_i) &= \begin{bmatrix} x_{4,i}^2 + u_i \\ x_{1,i}x_{2,i} + x_{3,i}^2 u_i \\ 3u_i^2 \\ (x_{2,i} - 2x_{1,i} + 2x_{4,i})x_{4,i} - 2u_i^2 \end{bmatrix}. \end{aligned} \quad (26)$$

The system satisfies the assumption (4) since

$$\begin{aligned} \det[Ez - A_\alpha] &= \det[E(z - \alpha) - A] \\ &= \begin{vmatrix} -1 & 0 & 0 & z - 1.5 \\ 0 & z - 0.5 & -1 & 0 \\ z + 0.5 & 2z - 2 & 0 & z - 0.5 \\ 0 & -z - 1.5 & -1 & -1 \end{vmatrix} \\ &= -2z^3 - z^2 + 4.5z - 0.75 \neq 0. \end{aligned} \quad (27)$$

Using Procedure 2 we obtain the following:

Step 1. Interchanging the first and fourth columns of the matrix C , we obtain

$$\begin{aligned} \hat{C} &= CQ_0 \\ &= \begin{bmatrix} 0 & 0 & 0 & 1 \\ 0 & 1 & 0 & 0 \\ 0 & 0 & 1 & 0 \\ 1 & 0 & 0 & 0 \end{bmatrix} \\ &= [C_1 \quad C_2], \\ C_1 &= \begin{bmatrix} 1 & 0 \\ 2 & 1 \end{bmatrix}, \quad C_2 = \begin{bmatrix} 0 & 0 \\ 0 & 2 \end{bmatrix} \end{aligned} \quad (28)$$

and

$$\begin{aligned} \bar{C} &= \hat{C}Q_2 = [C_1 \quad C_2] \begin{bmatrix} C_1^{-1} & -C_1^{-1}C_2 \\ 0 & I_{n-p} \end{bmatrix} \\ &= \begin{bmatrix} 1 & 0 & 0 & 0 \\ 2 & 1 & 0 & 2 \end{bmatrix} \begin{bmatrix} 1 & 0 & 0 & 0 \\ -2 & 1 & 0 & -2 \\ 0 & 0 & 1 & 0 \\ 0 & 0 & 0 & 1 \end{bmatrix} \\ &= \begin{bmatrix} 1 & 0 & 0 & 0 \\ 0 & 1 & 0 & 0 \end{bmatrix}, \end{aligned} \quad (29)$$

$$Q_1 = Q_0 Q_2 = \begin{bmatrix} 0 & 0 & 0 & 1 \\ -2 & 1 & 0 & -2 \\ 0 & 0 & 1 & 0 \\ 1 & 0 & 0 & 0 \end{bmatrix}. \quad (30)$$

Step 2. The new state vector has the form

$$\begin{aligned} \bar{x}_i = Q_1^{-1} x_i &= \begin{bmatrix} 0 & 0 & 0 & 1 \\ -2 & 1 & 0 & -2 \\ 0 & 0 & 1 & 0 \\ 1 & 0 & 0 & 0 \end{bmatrix}^{-1} \begin{bmatrix} x_{1,i} \\ x_{2,i} \\ x_{3,i} \\ x_{4,i} \end{bmatrix} \\ &= \begin{bmatrix} x_{4,i} \\ 2x_{1,i} + x_{2,i} + 2x_{4,i} \\ x_{3,i} \\ x_{1,i} \end{bmatrix} = \begin{bmatrix} \bar{x}_{1,i} \\ \bar{x}_{2,i} \end{bmatrix} \end{aligned} \quad (31)$$

and the subvector $\bar{x}_{1,i}$ is known since $y_i = \bar{x}_{1,i}$, $i \in \mathbb{Z}_+$. Therefore, the reduced-order perfect observer should reconstruct only the subvector $\bar{x}_{2,i}$. In this case we have

$$P_1 = \begin{bmatrix} 1 & 0 & 0 & 0 \\ 0 & 0 & 2 & 3 \\ 0 & 1 & -1 & 0 \\ 0 & 3 & -2 & 0 \end{bmatrix} \quad (32)$$

and

$$\begin{aligned} P_1 E Q_1 &= \begin{bmatrix} 1 & 0 & 0 & 0 \\ 0 & 0 & 2 & 3 \\ 0 & 1 & -1 & 0 \\ 0 & 3 & -2 & 0 \end{bmatrix} \begin{bmatrix} 0 & 0 & 0 & 1 \\ 0 & 1 & 0 & 0 \\ 1 & 2 & 0 & 1 \\ 0 & -1 & 0 & 0 \end{bmatrix} \\ &\times \begin{bmatrix} 0 & 0 & 0 & 1 \\ -2 & 1 & 0 & -2 \\ 0 & 0 & 1 & 0 \\ 1 & 0 & 0 & 0 \end{bmatrix} \\ &= \begin{bmatrix} 1 & 0 & 0 & 0 \\ 0 & 1 & 0 & 0 \\ 1 & -1 & 0 & 1 \\ 0 & -1 & 0 & 0 \end{bmatrix} \\ &= \begin{bmatrix} E_{11} & 0 \\ E_{21} & E_{22} \end{bmatrix}, \\ E_{11} &= \begin{bmatrix} 1 & 0 \\ 0 & 1 \end{bmatrix}, \quad E_{21} = \begin{bmatrix} 1 & -1 \\ 0 & -1 \end{bmatrix}, \\ E_{22} &= \begin{bmatrix} 0 & 1 \\ 0 & 0 \end{bmatrix}, \end{aligned} \quad (33)$$

$$\begin{aligned} P_1 A_\alpha Q_1 &= \begin{bmatrix} 1 & 0 & 0 & 0 \\ 0 & 0 & 2 & 3 \\ 0 & 1 & -1 & 0 \\ 0 & 3 & -2 & 0 \end{bmatrix} \begin{bmatrix} 1 & 0 & 0 & 1.5 \\ 0 & 0.5 & 1 & 0 \\ -0.5 & 2 & 0 & 0.5 \\ 0 & 1.5 & 1 & 1 \end{bmatrix} \\ &\times \begin{bmatrix} 0 & 0 & 0 & 1 \\ -2 & 1 & 0 & -2 \\ 0 & 0 & 1 & 0 \\ 1 & 0 & 0 & 0 \end{bmatrix} \\ &= \begin{bmatrix} 1.5 & 0 & 0 & 1 \\ -13 & 8.5 & 3 & -18 \\ 2.5 & -1.5 & 1 & 3.5 \\ 4 & -2.5 & 3 & 6 \end{bmatrix} \\ &= \begin{bmatrix} A_{11} & A_{12} \\ A_{21} & A_{22} \end{bmatrix}, \\ A_{11} &= \begin{bmatrix} 1.5 & 0 \\ -13 & 8.5 \end{bmatrix}, \quad A_{12} = \begin{bmatrix} 0 & 1 \\ 3 & -18 \end{bmatrix} \\ A_{21} &= \begin{bmatrix} 2.5 & -1.5 \\ 4 & -2.5 \end{bmatrix}, \quad A_{22} = \begin{bmatrix} 1 & 3.5 \\ 3 & 6 \end{bmatrix}, \end{aligned} \quad (34)$$

$$\begin{aligned} P_1 f(x_i, u_i) &= \begin{bmatrix} 1 & 0 & 0 & 0 \\ 0 & 0 & 2 & 3 \\ 0 & 1 & -1 & 0 \\ 0 & 3 & -2 & 0 \end{bmatrix} \\ &\times \begin{bmatrix} x_{4,i}^2 + u_i \\ x_{1,i}x_{2,i} + x_{3,i}^2 u_i \\ 3u_i^2 \\ (x_{2,i} - 2x_{1,i} + 2x_{4,i})x_{4,i} - 2u_i^2 \end{bmatrix} \\ &= \begin{bmatrix} x_{4,i}^2 + u_i \\ 3(x_{2,i} - 2x_{1,i} + 2x_{4,i})x_{4,i} \\ x_{1,i}x_{2,i} + x_{3,i}^2 u_i - 3u_i^2 \\ 3x_{1,i}x_{2,i} + 3x_{3,i}^2 u - 6u_i^2 \end{bmatrix} \\ &= \begin{bmatrix} f_1(\bar{x}_{1,i}, u_i) \\ f_2(\bar{x}_i, u_i) \end{bmatrix}, \\ f_1(\bar{x}_{1,i}, u_i) &= \begin{bmatrix} x_{4,i}^2 + u_i \\ 3(x_{2,i} - 2x_{1,i} + 2x_{4,i})x_{4,i} \end{bmatrix}, \\ f_2(\bar{x}_i, u_i) &= \begin{bmatrix} x_{1,i}x_{2,i} + x_{3,i}^2 u_i - 3u_i^2 \\ 3x_{1,i}x_{2,i} + 3x_{3,i}^2 u - 6u_i^2 \end{bmatrix}. \end{aligned} \quad (35)$$

The descriptor subsystem (24) is given by the equations

$$\begin{aligned} &\begin{bmatrix} 0 & 1 \\ 0 & 0 \end{bmatrix} \bar{x}_{2,i+1} \\ &= \begin{bmatrix} 1 & 3.5 \\ 3 & 6 \end{bmatrix} \bar{x}_{2,i} \\ &+ \sum_{j=2}^{i+1} (-1)^{j+1} \begin{pmatrix} 0.5 \\ j \end{pmatrix} \begin{bmatrix} 0 & 1 \\ 0 & 0 \end{bmatrix} \bar{x}_{2,i-j+1} \\ &+ \begin{bmatrix} x_{1,i}x_{2,i} + x_{3,i}^2 u_i - 3u_i^2 \\ 3x_{1,i}x_{2,i} + 3x_{3,i}^2 u - 6u_i^2 \end{bmatrix}, \end{aligned} \quad (36a)$$

$$\bar{y}_i = \begin{bmatrix} 0 & 1 \\ 3 & -18 \end{bmatrix} \bar{x}_{2,i}, \quad (36b)$$

where

$$\begin{aligned} \bar{y}_i = & \begin{bmatrix} 1 & 0 \\ 0 & 1 \end{bmatrix} \bar{x}_{1,i+1} \\ & - \sum_{j=2}^{i+1} (-1)^{j+1} \begin{pmatrix} 0.5 \\ j \end{pmatrix} \begin{bmatrix} 1 & 0 \\ 0 & 1 \end{bmatrix} \bar{x}_{1,i-j+1} \\ & - \begin{bmatrix} x_{4,i}^2 + u_i \\ 3(x_{2,i} - 2x_{1,i} + 2x_{4,i})x_{4,i} \end{bmatrix}. \end{aligned} \quad (36c)$$

Step 3. Using Procedure 1, we obtain the following. We have

$$N = \begin{bmatrix} 0 & 1 \\ 0 & 0 \end{bmatrix}, \quad \bar{A} = A_{22} + \alpha N, \quad \bar{C} = A_{12}$$

and we choose

$$D = \begin{bmatrix} 3 & 0 \\ 0 & 4 \end{bmatrix}.$$

Note that the condition (14) is satisfied and the equation (15) has the form

$$\begin{aligned} HA_{12} &= H \begin{bmatrix} 0 & 1 \\ 3 & -18 \end{bmatrix} \\ &= A_{22} + \alpha N - D = \begin{bmatrix} 1 & 4 \\ 3 & 2 \end{bmatrix}. \end{aligned} \quad (37)$$

Its solution is

$$H = \begin{bmatrix} 10 & \frac{1}{3} \\ 20 & 1 \end{bmatrix}. \quad (38)$$

Using (16), we obtain in our case

$$\begin{aligned} F &= A_\alpha - HA_{12} \\ &= \begin{bmatrix} 4 & 4 \\ 3 & 6 \end{bmatrix} - \begin{bmatrix} 10 & \frac{1}{3} \\ 20 & 1 \end{bmatrix} \begin{bmatrix} 0 & 1 \\ 3 & -18 \end{bmatrix} \\ &= \begin{bmatrix} 3 & 0 \\ 0 & 4 \end{bmatrix}. \end{aligned} \quad (39)$$

The desired reduced-order perfect observer is described by

$$\begin{aligned} & \begin{bmatrix} 0 & 1 \\ 0 & 0 \end{bmatrix} \hat{x}_{i+1} \\ &= \begin{bmatrix} 3 & 0 \\ 0 & 4 \end{bmatrix} \hat{x}_i \\ &+ \sum_{j=2}^{i+1} (-1)^{j+1} \begin{pmatrix} 0.5 \\ j \end{pmatrix} \begin{bmatrix} 0 & 1 \\ 0 & 0 \end{bmatrix} x_{i-j+1} \\ &+ f_2(\bar{x}_i, u_i) + \begin{bmatrix} 10 & \frac{1}{3} \\ 20 & 1 \end{bmatrix} \bar{y}_i. \end{aligned} \quad (40)$$

◆

5. Concluding remarks

Reduced-order perfect fractional descriptor nonlinear observers for fractional descriptor discrete-time nonlinear systems have been proposed. Conditions for the existence of the reduced-order perfect observers have been established (Theorem 2). A procedure for designing the reduced-order perfect observers has been proposed and illustrated with a numerical example.

An open problem is the extension of those considerations to fractional continuous-discrete nonlinear systems and to positive continuous-time and discrete-time nonlinear systems.

Acknowledgment

This work was supported by the National Science Centre in Poland under the grant no. 2014/13/B/ST7/03467.

References

- Cuihong, W. (2012). New delay-dependent stability criteria for descriptor systems with interval time delay, *Asian Journal of Control* **14**(1): 197–206.
- Dodig, M. and Stosic, M. (2009). Singular systems state feedbacks problems, *Linear Algebra and Its Applications* **431**(8): 1267–1292.
- Dai, L. (1989). *Singular Control Systems*, Springer, Berlin.
- Duan, G.R. (2010). *Analysis and Design of Descriptor Linear Systems*, Springer, New York, NY.
- Fahmy, M.M. and O'Reill, J. (1989). Matrix pencil of closed-loop descriptor systems: Infinite-eigenvalues assignment, *International Journal of Control* **49**(4): 1421–1431.
- Gantmacher, F.R. (1959). *The Theory of Matrices*, Chelsea, London.
- Kaczorek, T. (1992). *Linear Control Systems*, Wiley, New York, NY.
- Kaczorek, T. (2001). Full-order perfect observers for continuous-time linear systems, *Bulletin of the Polish Academy of Sciences: Technical Sciences* **49**(4): 549–558.
- Kaczorek, T. (2004). Infinite eigenvalue assignment by an output feedback for singular systems, *International Journal of Applied Mathematics and Computer Science* **14**(1): 19–23.
- Kaczorek, T. (2008). Fractional positive continuous-time linear systems and their reachability, *International Journal of Applied Mathematics and Computer Science* **18**(2): 223–228, DOI: 10.2478/v10006-008-0020-0.
- Kaczorek, T. (2011a). Positive linear systems consisting of n subsystems with different fractional orders, *IEEE Transaction on Circuits and Systems* **58**(7): 1203–1210.
- Kaczorek, T. (2011b). *Selected Problems of Fractional Systems Theory*, Springer, Berlin.
- Kaczorek, T. (2012a). Checking of the positivity of descriptor linear systems with singular pencils, *Archives of Control Sciences* **22**(1): 77–86.

- Kaczorek T. (2012b). Positive fractional continuous-time linear systems with singular pencils, *Bulletin of the Polish Academy of Sciences: Technical Sciences* **60**(1): 9–12.
- Kaczorek, T. (2013). Descriptor fractional linear systems with regular pencils, *Asian Journal of Control* **15**(4): 1051–1064.
- Kaczorek, T. (2014a). Fractional descriptor observers for fractional descriptor continuous-time linear systems, *Archives of Control Sciences* **24**(1): 27–37.
- Kaczorek, T. (2014b). Reduced-order fractional descriptor observers for fractional descriptor continuous-time linear systems, *Bulletin of the Polish Academy of Sciences: Technical Sciences* **62**(4): 889–895.
- Kaczorek, T. (2015). Perfect observers of fractional descriptor continuous-time linear systems, in K. Latawiec, et al. (Eds.), *Advances in Modeling and Control of Non-integer Orders Systems*, Springer, Cham, pp. 3–12.
- Kaczorek, T. (2016a). Perfect nonlinear observers of descriptor discrete-time nonlinear systems, *Asian Journal of Control*, (submitted).
- Kaczorek, T. (2016b). Perfect nonlinear observers of fractional descriptor continuous-time nonlinear systems, *Fractional Calculus and Applied Analysis* **19**(3): 775–784.
- Kaczorek, T. (2016c). Positivity and stability of fractional descriptor time-varying discrete-time linear systems, *International Journal of Applied Mathematics and Computer Science* **26**(1): 5–13, DOI: 10.1515/amcs-2016-0001.
- Kaczorek, T. (2016d). Reduced-order fractional descriptor observers for a class of fractional descriptor continuous-time nonlinear systems, *International Journal of Applied Mathematics and Computer Science* **26**(2): 277–283, DOI: 10.1515/amcs-2016-0019.
- Kociszewski, R. (2013). Observer synthesis for linear discrete-time systems with different fractional orders, *Pomiary Automatyka Robotyka* **17**(2): 376–381.
- Kucera, V. and Zagalak, P. (1988). Fundamental theorem of state feedback for singular systems, *Automatica* **24**(5): 653–658.
- Lewis, F.L. (1983). Descriptor systems, expanded descriptor equation and Markov parameters, *IEEE Transactions on Automatic Control* **28**(5): 623–627.
- Luenberger, D.G. (1977). Dynamical equations in descriptor form, *IEEE Transactions on Automatic Control* **22**(3): 312–321.
- Luenberger, D.G. (1978). Time-invariant descriptor systems, *Automatica* **14**(5): 473–480.
- N'Doye, I., Darouach, M., Voos, H. and Zasadzinski, M. (2013). Design of unknown input fractional-order observers for fractional-order systems, *International Journal of Applied Mathematics and Computer Science* **23**(3): 491–500, DOI: 10.2478/amcs-2013-0037.
- Oldham, K.B. and Spanier, J. (1974). *The Fractional Calculus*, Academic Press, New York, NY.
- Ostalczyk, P. (2008). *Epitome of the Fractional Calculus: Theory and Its Applications in Automatics*, Łódź University of Technology Publishing House, Łódź, (in Polish).
- Podlubny, I. (1999). *Fractional Differential Equations*, Academic Press, New York, NY.
- Sajewski, Ł. (2016). Descriptor fractional discrete-time linear system with two different fractional orders and its solution, *Bulletin of the Polish Academy of Sciences: Technical Sciences* **64**(1): 15–20.
- Van Dooren, P. (1979). The computation of Kronecker's canonical form of a singular pencil, *Linear Algebra and Its Applications* **27**: 103–140.
- Vinagre, B.M., Monje, C.A. and Calderon, A.J. (2002). Fractional order systems and fractional order control actions, *IEEE Conference on Decision and Control, Las Vegas, NV, USA*, pp. 2550–2554.
- Virnik, E. (2008). Stability analysis of positive descriptor systems, *Linear Algebra and Its Applications* **429**(10): 2640–2659.



Tadeusz Kaczorek received the M.Sc., Ph.D. and D.Sc. degrees in electrical engineering from the Warsaw University of Technology in 1956, 1962 and 1964, respectively. In the years 1968–1969 he was the dean of the Electrical Engineering Faculty, and in the period of 1970–1973 he was a deputy rector of the Warsaw University of Technology. In 1971 he became a professor and in 1974 a full professor at the same university. Since 2003 he has been a professor at the Białystok University of Technology. In 1986 he was elected a corresponding member and in 1996 a full member of the Polish Academy of Sciences. In the years 1988–1991 he was the director of the Research Center of the Polish Academy of Sciences in Rome. In 2004 he was elected an honorary member of the Hungarian Academy of Sciences. He has been granted honorary doctorates by 13 universities. His research interests cover systems theory, especially singular multidimensional systems, positive multidimensional systems, singular positive 1D and 2D systems, as well as positive fractional 1D and 2D systems. He initiated research in the field of singular 2D, positive 2D and positive fractional linear systems. He has published 28 books (8 in English) and over 1100 scientific papers. He has also supervised 69 Ph.D. theses. He is the editor-in-chief of the *Bulletin of the Polish Academy of Sciences: Technical Sciences* and a member of editorial boards of ten international journals.

Received: 27 October 2016

Revised: 23 January 2017

Re-revised: 4 February 2017

Accepted: 25 March 2017