THE RADIATION PROBLEM FROM A VERTICAL SHORT DIPOLE ANTENNA ABOVE FLAT AND LOSSY GROUND: COMPARISON OF EXACT ANALYTICAL SOLUTIONS WITH EMPIRICAL TERRAIN PROPAGATION MODELS AND INVESTIGATION OF SURFACE WAVES

Georgi BEBROV, Sotiris BOURGIOTIS, Ariadni CHRYSOSTOMOU,
Panayiotis FRANGOS

National Technical University of Athens , Athens, Greece
pfrangos@central.ntua.gr

Abstract: The results of a recently introduced novel solution to the well-known ‘Sommerfeld radiation problem’ are compared to those obtained through the classical Sommerfeld formulation. The method is novel in that it is entirely performed in the frequency domain, yielding simple integral expressions for the received Electromagnetic (EM) field and also in that they can end up into closed-form analytic formulas applicable to high frequencies. In this paper we compare our analytical results with existing theoretical calculations found in the literature, based on the Sommerfeld formulation. The above comparison shows good agreement in the corresponding numerical results. Furthermore, a comparison of the method to the well-known Okumura-Hata empirical model is performed in an attempt to roughly estimate the extent to which the proposed model is suitable for real-environment EM field calculations. Finally, preliminary investigations by our research group on the behaviour of the surface waves will be presented.

Keywords: Wireless Communications, Electromagnetic Waves Propagation Models

1. Introduction

The ‘Sommerfeld radiation problem’ is a well-known problem in the area of propagation of electromagnetic (EM) waves above flat and lossy ground [1]. The original Sommerfeld solution to this problem is provided in the physical space by using the ‘Hertz potentials’ and it does not end up with closed-form analytical solutions.

In [2], the authors considered the problem from a spectral domain perspective, which led to relatively simple 1-D integral representations for the received EM field. Then with the use of the Stationary Phase Method (SPM, [2]) novel, closed-form analytic formulas were derived, applicable in the high frequency regime.

The comparison between the analytical expressions of [2] and their integral

counterparts was performed in [3] where the requirements for the applicability of the SPM method were extracted. However, as mentioned there, due to the peculiarities of the integrands, which possess particular singularities, the integral expressions of [2] are not easily evaluated using standard numerical integration techniques, as for example the adaptive Simpson’s method used in [3]. As a result, a confirmation of the results by using alternative integral evaluation techniques is justified. In this work, the results for the received EM field, taken via the application of the previously mentioned SPM method are juxtaposed against the ones available in a related research work [4]. The latter are obtained via ‘a claimed to be accurate’ evaluation of the original Sommerfeld integrals using commercially available simulation

software, namely AWAS [4].

The last part of this work is devoted to comparing the above mentioned SPM-based analytical expressions to a well-known empirical model for path loss prediction, particularly Okumura - Hata [5]. This, as well as similar comparisons to be performed in the future, will eventually determine the extent to which the easily implemented model of [2] can be used for the purposes of radio wave coverage prediction in real life scenarios.

2. Problem geometry

The problem geometry is shown in Fig. 1. A vertical Hertzian Dipole (HD), of dipole

Figure 1: Geometry of the problem

In Fig. 1, point A' is the image of the HD with respect to the ground, r_1 is the distance between the source and the observation point (OP), $r_2=(A'A)$ the distance between the image and the OP, θ the 'angle of incidence' at the so-called 'specular point' and $\varphi=\pi/2-\theta$ the so-called 'grazing angle'.

3. Integral representations for the received electric field and analytic expressions in the high freq. regime

In [2] it is shown that the electric field at the receiver's position above the ground level ($x>0$) can be expressed with the following integral formula ($\underline{E}^{LOS}$ denotes the direct field),

$$\underline{E}(\underline{r}) = \underline{E}^{LOS}(\underline{r}) - \frac{ip}{8\pi\epsilon_{r1}\epsilon_0} \times \left\{ \hat{e}_\rho \int_{-\infty}^{\infty} k_\rho^2 \frac{\epsilon'_{r2}\kappa_1 - \epsilon_{r1}\kappa_2}{\epsilon'_{r2}\kappa_1 + \epsilon_{r1}\kappa_2} e^{ik_1(x+x_0)} \cdot H_0^{(1)}(k_\rho\rho) dk_\rho - \right.$$

moment p , directed to the positive x axis, at altitude x_0 above infinite, flat, lossy ground radiates time-harmonic electromagnetic (EM) waves at angular frequency $\omega=2\pi f$ ($e^{-i\omega t}$ time dependence is assumed). The relative complex permittivity of the ground is $\epsilon'_r = \epsilon'/\epsilon_0 = \epsilon_r + i\sigma/\omega\epsilon_0$, σ being the ground conductivity, f the carrier frequency and $\epsilon_0 = 8,854 \times 10^{-12} \text{ F/m}$ the absolute permittivity in vacuum or air. The wavenumbers of propagation are:

$$k_{01} = \omega/c_1 = \omega\sqrt{\epsilon_1\mu_1} = \omega\sqrt{\epsilon_0\mu_0} \quad (1)$$

$$k_{02} = \omega/c_2 = \omega\sqrt{\epsilon_2\mu_2} = k_{01}\sqrt{\epsilon_r + i(\sigma/\omega\epsilon_0)} \quad (2)$$

$$- \hat{e}_x \int_{-\infty}^{\infty} k_\rho^3 \frac{\epsilon'_{r2}\kappa_1 - \epsilon_{r1}\kappa_2}{\kappa_1(\epsilon'_{r2}\kappa_1 + \epsilon_{r1}\kappa_2)} e^{ik_1(x+x_0)} \cdot H_0^{(1)}(k_\rho\rho) dk_\rho \left\} \quad (3)$$

where:

$$\kappa_1 = \sqrt{k_{01}^2 - k_\rho^2}, \kappa_2 = \sqrt{k_{02}^2 - k_\rho^2} \quad (4)$$

and $H_0^{(1)}$ is the Hankel function of first kind and zero order. Application of SPM to (3), leads to the following analytic expressions for the electric field vector scattered from the plane ground, in the far field region and in the high frequency regime (for $x>0$) [3]:

$$\underline{E}_{x>0}^{sc} = \frac{pk_{01} \cos \varphi}{4\pi\epsilon_0\epsilon_{r1}(A'A)} \cdot \frac{\epsilon'_{r2}\kappa_{1s} - \epsilon_{r1}\kappa_{2s}}{\epsilon'_{r2}\kappa_{1s} + \epsilon_{r1}\kappa_{2s}} \cdot e^{ik_{ps}\rho} \cdot e^{ik_{1s}(x+x_0)} \cdot (-\kappa_{1s}\hat{e}_\rho + k_{ps}\hat{e}_x) \quad (5)$$

where:

$$k_{ps} = \frac{k_{01}\rho}{\sqrt{(x+x_0)^2 + \rho^2}} = k_{01} \cos \varphi \quad (6)$$

$$\kappa_{1s} = \sqrt{k_{01}^2 - k_{ps}^2} = k_{01} \sin \varphi, \kappa_{2s} = \sqrt{k_{02}^2 - k_{ps}^2} \quad (7)$$

with k_{ps} being the stationary point obtained from the SPM method [2].

4. Comparisons with existing models

In this section various illustrations are presented, comparing the model of Section 3 with (i) the accurate Sommerfeld formulation, employed in related research work [4] and (ii) the Okumura – Hata empirical model for path loss prediction [5].

4.1 Comparison with Sommerfeld

formulation

Fig. 2 depicts the vertical component of the total received electric field, E_x , due to the radiation of a half wavelength, vertical dipole antenna above flat, lossy ground. The various plots refer to different transmitter heights. The set of the simulation parameters, used for the production of these plots, are shown in Table 1, above Fig. 2.

Table 1: Simulation Parameters

Symbol	Description	Value
f	Operating frequency	1GHz
x_0	Height of transmitting dipole	5m, 10m, 20m, 100m, 500 m
x	Height of observation point	2m
j	Distance range	1m – 50km
P	Radiated Power ¹	150W
$2h$	Length of the dipole antenna	$\lambda/2$
ϵ_r	Relative dielectric constant of ground (typical urban ground)	4.0
σ	ground conductivity	0.0002 S/m

¹ Used only in the simulated scenario of Section 3. The respective value used in [4] is not mentioned

Figure 2: Variation of the magnitude of the E_x component ($\mu V/m$) for various transmitting antenna heights

The right plot of Fig. 2 refers to the field values according to the analytical expressions (5) – (7), whereas the right one gives the respective results obtained after evaluating the ‘Sommerfeld integrals’ for the total received EM field [4].

Evidently, the results are in very good agreement. The SPM-based analytical method of Section 3 predicts the theoretical field behavior and this is true both for the near field as well as the far field region, as they are defined in [4]. In this regard, the

so-claimed in [3], ‘high frequency regime analytical method’ of [2], is validated for such high frequencies as 1GHz.

As another validation of the previous arguments, Fig. 3 depicts the behavior of the electric field, for various scenarios regarding the electrical parameters of the ground, as shown in Table 2, beside Fig. 3. The field behavior shown in Fig. 3 is almost identical to that presented in Fig. 7 of [4], which is the equivalent case to the scenario considered here. In other words, the

analytic expressions (5) – (7) validate the important finding of [4] (reached by numerical evaluation of the ‘Sommerfeld

integrals’), namely the fact that the type of the ground does not influence significantly the received EM field values.

Table 2: Simulation parameters

Parameter	Value	
Operating frequency	900MHz	
Height of transmitting dipole	5m	
Height of observation point	2m	
Distance range	1m – 50km	
Radiated Power ¹	150 W	
Length of the dipole antenna	$\lambda/2$	
<i>Ground Parameters</i>	ϵ_r	σ (S/m)
Poor urban ground	4	0.001
Average ground	15	0.005
Good ground	25	0.02
Fresh water	81	0.01
Sea water	81	5.0

¹ Used only in the simulated scenario of Section 3.

Figure 3: Variation of the magnitude of the E_x component ($\text{dB}\mu\text{V/m}$) for various ground types

4.2 Comparison with Okumura Hata empirical model

A preliminary check of the model proposed hereby against the well-known Okumura – Hata (OH) empirical model [5], commonly used for predicting signal loss in land mobile radio services, is carried out. Fig. 4 below illustrates the comparison.

From Fig.4 it is evident that the proposed model exhibits similar behavior to the

Okumura – Hata model for the case of an open (rural) area. On the contrary, there is an appreciable mismatch between them when applied to urban or suburban environments. A correction factor to accommodate for the specifics of the propagation environment (i.e. the presence of buildings, foliage, obstacles etc – typical to urban/suburban environment) is required and will be the subject of future research.

Figure 4: Comparisons with OH model for urban (urb), suburban (sub) and rural (rur) environments

5. Conclusion – Future research

In this work, a comparison of a recently introduced solution to the ‘Sommerfeld radiation problem, in the spectral domain’, against theoretical as well as empirical approaches for the given problem is demonstrated. The proposed model leads to easily implemented analytical expressions

for the received EM field and is proved to be valid in the high frequency regime.

Further validations against theoretically driven numerical results, like those of [4] used here, are required to determine the exact frequency limits of the analytic expressions (5) – (7). For this, the perspective described in [3], which is

believed to reduce the precision errors in the evaluation of the integral expressions, will be followed, leading also to a novel spectral domain representation for the so called surface wave as well [note that (5) neglects the role of the surface wave]. For this particular issue, ongoing research is carried out by our research group [6], through which the integral representation for the EM field (3) is evaluated by means of a contour integral in the complex plane, as shown in Fig. 5. This approach has the additional advantage that it considers the effect of the pole's position (i.e. the position of the integrand's singularity) in relation to the contour of integration and as

a result it is expected to yield more accurate asymptotic approximations for the received EM field. In [6] the particular case where $\sigma \gg \omega \epsilon_0$ is analyzed and fully analytic expressions for the EM field are derived, including the contribution of the surface waves.

Finally, an attempt to identify the necessary corrections that will extend the model's applicability to more complex environments is also planned. Such checks will eventually determine the adoptions necessary for turning the novel propagation model of [2] to a robust prediction tool appropriate for radio planning purposes.

Figure 5: Complex Plane Contour Integration for the EM field

References

- [1] A. N. Sommerfeld, *Propagation of Waves in Wireless Telegraphy*, Ann. Phys., 28, pp. 665–736, March 1909; and 81, pp. 1135–1153, December 1926.
- [2] K. Ioannidi, Ch. Christakis, S. Sautbekov, P. Frangos and S.K. Atanov, *The radiation problem from a vertical Hertzian dipole antenna above flat and lossy ground: novel formulation in the spectral domain with closed-form analytical solution in the high frequency regime*, International Journal Antennas and Propagation, Hindawi Ed. Co., Special Issue ‘Propagation of electromagnetic (EM) waves over terrain’ (PEWT), vol. 2014..
- [3] A. Chrysostomou, S. Bourgiotis, S.Sautbekov, K. Ioannidi and P. Frangos, *Radiation of a Vertical Dipole Antenna over Flat and Lossy Ground: Accurate Electromagnetic Field Calculation using the Spectral Domain Approach along with Redefined Integral Representations and corresponding Novel Analytical Solution*, Electronics and Electrical Engineering Journal, Vol. 22, No. 2, 2016.
- [4] T. K. Sarkar et. al., *Electromagnetic Macro Modelling of Propagation in Mobile Wireless Communication: Theory and Experiment*, IEEE Antennas and Propagation Magazine, Vol. 54, No. 6, pp. 17–43, Dec. 2012.

- [5] Hata, Masaharu, *Empirical formula for propagation loss in land mobile radio services*, IEEE Transactions on Vehicular Technology, Vol.VT-29, No.3, pp.317 – 325, August 1980.
- [6] S. Sautbekov, S. Bourgiotis, A. Chrysostomou and P. Frangos, *A Novel Asymptotic Solution to the Sommerfeld Radiation Problem: Analytic field expressions and the emergence of the Surface Waves*, Progress In Electromagnetics Research (PIER), 2017 (unpublished)